

## HCVR-3 CONVENTIONAL RELEASING FIRE ALARM CONTROL PANEL



### DESCRIPTION

The HCVR-3 is a 3 zone conventional releasing fire alarm control panel that is UL Listed and FM Approved for releasing.

The HCVR-3 can be configured to activate releasing by a single zone or combination of any two zones. The LCD display is used to show the countdown timer during activation of the releasing sequence.

The HCVR-3 is fully programmable using simple menu options. The panel is a single board construction which provides an easy replacement solution. It is also compatible with a wide range of devices.

### STANDARD FEATURES

- UL 864 Listed and FM Approved
- Three detection zones
- Any single zone or any combination of zones can be configured to release
- Fully programmable using simple menu options
- Simple, single board construction
- Installer friendly
- Compatible with wide range of detection devices
- Configurable first stage NAC delays
- Configurable detection delays
- Built-in Manual Release switch and separate circuit
- Compatible with FirePro® Xtinguish
- Compatible with various releasing valves
- Configurable releasing delays up to 60 seconds in 5 second intervals
- Configurable releasing duration up to 5 minutes in 5 second intervals
- Releasing countdown timer displayed on the LCD
- Supports up to seven HCVR-SDU or HCVR-AB
- Built-in relays for Fire, Trouble, Stage 1, Stage 2, Extract and Local Fire

*Specifications subject to change without notice.*

### PRODUCT LISTINGS

SIGNALING



California State  
Fire Marshal  
7165-0410:0206



3046396

### Hochiki America Corporation

7051 Village Drive, Suite 100 Buena Park, CA 90621-2268

Phone: 714/522-2246 Fax: 714/522-2268

Technical Support: 800-845-6692 or [technicalsupport@hochiki.com](mailto:technicalsupport@hochiki.com)

Find latest revision at [www.hochiki.com](http://www.hochiki.com)



## SPECIFICATIONS

Supply Voltage	115VAC (50hz/60hz) or 230VAC (50hz/60hz)
Power Supply DC Rating	24VDC 3 Amps total including battery charging
Mains Supply Fuse	1.6 Amps 250VAC, slow-blow, 5 x 20mm
Dimensions	15.2" (385mm)W x 12.2" (310mm)H x 3.5" (90mm)D
Weight	12.3 lbs.
Color	Red or gray
Material	1.2mm mild steel
Max. Battery Size	7Ah 12V (2 per panel)
RS-485 Serial Bus	Maximum line impedance 120 Ohms
Trouble Contact Rating	30VDC 1 Amp
Local Fire Contact Rating	30VDC 1 Amp
Fire Contact Rating	30VDC 1 Amp
1st Stage Contact Rating	30VDC 1 Amp
2nd Stage Contact Rating	30VDC 1 Amp
EXTING Contact Rating	30 VDC 1 Amp contacts for (NO) and (C)
EXTING Contact Rating	18 to 28VDC 1 Amp max load for 5 minutes and voltage reversing DC
NAC Output Rating	0.5 Amp per output
Detection Zone End of line resistor	6K8 Ohms 5% resistor
NAC Output	10K Ohms 5% resistor
Stand by Current	86 mA
Alarm Current	620 mA
Operating Humidity	93% (non condensing)
Operating Temperature	-5°C to +40°C

## HOCHIKI AMERICA COMPATIBLE DEVICES

MODEL	DESCRIPTION	MAX
<b>PANEL ACCESSORIES</b>		
HCVR-SDU	Remote Status Display Unit	7
HCVR-AB	Ancillary Board	7
HCVR-SQA	Sequential Activator	20
HCVR-DS	Disconnect Switch	1
<b>DETECTORS</b>		
SLR-24H	Photoelectric Smoke Detector w/heat	20
SLR-835	Photoelectric 8-35V Smoke Detector	20
SLR-835/-835W	Photoelectric 8-35V Smoke Detector	20
SLR-835-BH-2W	Photoelectric 8-35V Smoke Detector w/heat	20
SLV-24V/-24/-24N	Photoelectric Smoke Detector	20
SIJ-24	Ionization Smoke Detector	20
DCD-135	135° Fixed Temperature Rate of Rise Heat Detector	20
DCD-190	190° Fixed Temperature Rate of Rise Heat Detector	20
<b>BASES</b>		
NS6-220	6" base, 43mA draw, 24V	20
NS4-220	4" base, 43mA draw, 24V	20
<b>PULL STATION/ABORT SWITCH</b>		
HPS-SAK/HPS-DAH/HPS-SAH/HPS-DAK	Conventional Manual Pull Station	1
HCVR-AS	Abort Switch	1
<b>RELEASING VALVES</b>		
HV2185328	ASCO Solenoid	1
8210G207	ASCO Solenoid	1
11601	Viking Solenoid	1
11602	Viking Solenoid	1
11592	Viking Solenoid	1
11591	Viking Solenoid	1
11596	Viking Solenoid	1
11595	Viking Solenoid	1
2823A-2NB-A4F6	Snap-tite Solenoid	1
EA45 (510006)	Sevo Systems Solenoid	1
K-45-8017	Kidde Solenoid (equivalent to 486500-01)	1
B6793-859	Kidde Solenoid (equivalent to 81-100000-001)	1
753-E Series	Victaulic Solenoid	1
305350 Ci IS8B	Fire Eater Solenoid	1
305451 Ci IS8B	Fire Eater Solenoid	1